



Introduction

This QuickStart guide gives general guidelines and important precautions for getting your new 9555 Docking Station up and running quickly. Please see the complete 9555 Docking Station User's Manual for further details and operating instructions. The User's Manual is included with the product on CD ROM, or can be downloadable from www.ase-corp.com. For further information or clarification, please contact your service provider. Your Service Provider's tech support number should be included with this shipment.

Preparation: Remove Protective Antenna-Socket Plug

Before docking your 9555 Handset, it is **IMPERATIVE** that you remove and discard the rubberized packing plug from the antenna connector hole on the rear of the handset as shown. Held in by only a friction fit, the plug can be easily removed using a small screw driver.

IMPORTANT:

Failing to remove this plug may damage the docking station antenna connector.



Handset Configuration

Prior to docking, confirm the following settings on your Iridium handset;

- SIM card is installed and unlocked. Refer to your 9555 handset documentation for instructions.
- The 9555 handset firmware must be version **HT09007** or greater for proper operation in the Docking Station. Confirm by checking under Phone Setup (see handset documentation).

Antenna Location and Cable Lengths

Iridium antenna location and cable lengths are critical for successful installation and operation. Refer to the complete User's Manual for details.

Docking the Handset

1. Install the Docking Station in desired location and connect power and interface cables to the connectors located on the bottom. The antenna connector is located at the top and accepts a male TNC. See User's Manual for typical antenna cable types and their maximum lengths.
2. Remove antenna plug from handset (see Caution above).
3. Rotate the Secure Lock to the left to open.
4. Align the bottom of the 9555 handset with the Docking Station connector.
5. Press down slightly while rotating and seating the handset into the Dock.
6. Rotate the Secure Lock to the right to lock the handset in place.



Undocking the Handset

Simply rotate the Secure Lock to the left and remove handset.